



**Greenlamp®**

# **WIRELESS / WIFI Switch & Receiver**

# WIRELESS / WIFI Switch & Receiver



## PRODUCT FEATURES

- Kinetic switch control Paired with kinetic switch, single control and multi-control can be easily realized.
- Quick connect the terminal Without a screwdriver, press the quick connect button to insert the cable to complete the wiring
- Single control A wireless switch controls a single receiver
- Multiple control Two or more wireless switches control the same receiver
- Dimmer Use the double key switch to adjust the brightness of the dimmer
- Wireless or Wifi Connect


# WIRELESS / WIFI Switch & Receiver

DIMWS01

## Specifications

### SWITCH

Work type:	86 Push button type
Power mode:	kinetic energy, self-powered
Working frequency:	433MHZ
Keys:	1 GANG
Lifetime:	100,000 times
Dimensions:	80g
Distance:	80m(out door) 30m(in door)
Waterproof level:	IP65



### RECEIVER

Power consumptions:	<0.1W
Working temperature:	-10°C~40°C
Storage capacity:	10switch-keys
Power model:	AC100-240V,50/60hZ
Rated current:	100W LED 200W Resistive Loads
Weight:	50g
Dimension:	64*32*23mm
Distance:	80m(out door) 30m(indoor)
Waterproof level:	IP20